

## The Future of Analog IC Technology

## DESCRIPTION

The MP26058 is a linear, high performance single cell Li-Ion or Li-Polymer battery charger. By integrating high voltage input protection into the charger IC, the MP26058 can tolerate an input surge up to 28V. The LDO mode makes the MP26058 suitable for power up the system when battery is not present.

The device features constant current (CC) and constant voltage (CV) charging modes with programmable charge currents (200mA to 1A), current blocking. The other features include the programmable battery full indication threshold and the LDO mode operation which keeps charging the battery after battery-full is asserted and stay in full-state as long as the valid input is maintained. MP26058 can provide load to the system if no battery is connected.

For guaranteed safe operation, the MP26058 limits the die temperature to a preset value when the device is heated up due to limited PCB space. Other safety features are battery temperature monitoring, and programmable timer to prevent prolonged charging a dead battery.

MP26058 is available in 10-pin 3mm x 3mm DFN packages.

## **FEATURES**

- Complete Solution for Charging Single-Cell
   Lion-Ion Battery
- Input Surge Up to 28V
- Wide input operating range 2.8V 7V
- Adapter or USB Input
- Programmable Charge Current: 200mA to 1A
- Programmable timer
- 7V Input Over Voltage Protection
- 0.75% VBATT Accuracy over Temperature
- <1µA Battery Reverse Current
- 125µA Standby Current from V<sub>IN</sub>
- Battery Temperature Monitoring
- Automatic die temperature limiting
- Fault and Charge Status Indicators
- Soft-Start to limit inrush current
- Tiny 3mm x 3mm QFN Package

## APPLICATIONS

- Cell Phones
- Digital Cameras
- Smart Phones
- PDAs
- MP3 Players

"MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.







## PACKAGE REFERENCE



 For Tape & Reel, add suffix –Z (eg. MP26058DQ–Z) For RoHS compliant packaging, add suffix –LF (eg. MP26058DQ–LF–Z)

## ABSOLUTE MAXIMUM RATINGS (1)

IN to GND	V to +28V
All Other Pins to GND	V to +6.5V
ACOK & CHG Maximum Sink C	urrent20mA
Junction Temperature	140°C
Lead Temperature	260°C
Storage Temperature	65°C to +150°C

#### **Recommended Operating Conditions**<sup>(2)</sup>

Nominal Supply Voltage VIN	V to 5.5V
Operating Temperature	40°C to +85°C

Thermal Resistance <sup>(3)</sup>	θյΑ	θյς	

3x3 QFN10 ..... °C/W

#### Notes:

- 1) Exceeding these ratings may damage the device.
- 2) The device is not guaranteed to function outside of its
- operating conditions.3) Measured on JEDEC51-7 4 layer board...

# ELECTRICAL CHARACTERISTICS

 $V_{IN} = 5V$ ,  $V_{SHDN} = 0V$ ,  $T_A = +25^{\circ}C$ , unless otherwise noted.

Parameter	Symbol	Condition	Min	Тур	Max	Units
Supply Current	I <sub>SUPPLY</sub>	SHDN = High		30		μA
		SHDN = Low, I <sub>CHG</sub> = 0A		500		
Battery Voltage Regulation	V <sub>BATT</sub>	T = $-5^{\circ}$ C to +75 $^{\circ}$ C, I <sub>BATT</sub> = 0A	4.16	4.20	4.24	V
Constant Current Regulation	I <sub>CHG</sub>	$V_{IN}$ = 5V, $V_{BATT}$ = 3.8V R <sub>CHG</sub> = 3.3k $\Omega$	448	515	582	mA
Constant Current Variation		$V_{IN} = 5V, V_{BATT} = 3.8V,$ $T_J = 0^{\circ}C \text{ to } +120^{\circ}C,$ $R_{CHG} = 1.6k\Omega \text{ to } 8.0k\Omega$	87	100	113	%ICHG (4)
Battery Full Programming Range	I <sub>BF</sub>	Refer to Operation section for programming IBF	10		50	%ICHG (4)
IBF Accuracy			75		125	%IBF(5)
Input OVP		V <sub>IN</sub> Rising	6.7	7	7.3	V
OVP Hysteresis				400		mV
Input UVLO		V <sub>IN</sub> Rising	1.6	2.2	2.8	V
UVLO Hysteresis				100		mV
Input ACOK Up Range			6.7	7	7.2	V
ACOK & CHG Over Voltage Clamp	Vz			7.6		V



# ELECTRICAL CHARACTERISTICS (continued)

 $V_{IN}$  = 5V,  $V_{SHDN}$  =0V,  $T_A$  = +25°C, unless otherwise noted.

Parameter	Symbol	Condition	Min	Тур	Мах	Units
SHDN Trip Threshold High			2.6			V
SHDN Trip Threshold Low					0.4	V
CHG , ACOK Sink Current		Pin Voltage = 0.2V	5			mA
Battery Reverse Current to BATT Pin		SHDN = Low and Input = Floating or 0V			1	μA
Dropout Voltage	V <sub>IN</sub> - V <sub>BATT</sub>	$V_{BATT}$ = 3.8V, $R_{CHG}$ = 6k $\Omega$ . Current drop 10%		0.25		V
Soft Thermal Shutdown Threshold			105	120	135	°C
Soft Thermal Shutdown Hysteresis				10		°C
Internal Soft-Start Time		From 10% to 90% of full current		20		μs
R_NTC at 0°C	TH11- 4H104F	Note: R_NTC is 100k at 25°C		376.6		kΩ
R_NTC at 50°C	TH11- 4H104F	Note: R_NTC is 100k at 25°C		32.3		kΩ
Oscillation Freq		C <sub>TMR</sub> = 2.2uF		5		Hz
TMR Pin Source Current	I <sub>TMR1</sub>	V <sub>TMR</sub> =0.1V	18	20	22	μA
TMR Pin Sink Current	I <sub>TMR2</sub>	V <sub>TMR</sub> =1.5V	18	20	22	μA

Notes:

4) I<sub>CHG</sub> is the target preprogrammed charge current (Die temperature below 110°C).
5) I<sub>BF</sub> is the target preprogrammed battery full current threshold.





# **PIN FUNCTIONS**

Pin #	Name	Description
1	IN	Input Supply Pin. IN receives the AC adapter or USB supply voltage.
3	CHG	Open-Drain Charge Indicator. This pin is low during charging, is High after battery full or termination, is toggling the battery is fault.
2	ACOK	Open-Drain Fault Status Indicator.
4	TMR	Oscillator Period Timer. Connect a timing capacitor between this pin and GND to set the oscillator period. T(sec)=22000 * $C_{TMR}$ (µF). Short this pin to ground to disable timer.
5	GND, Exposed Pad	The exposed pad and GND pin must be connected to the same ground plane.
6	SHDN	Charger IC Enable. An input "Low" signal at this pin or if the pin is floating will enable the IC.
8	ISET	Constant Charge Current Program pin. Connect this pin to an external resistor to program the charging current in CC Mode.
7	IBF	Charge Status Threshold Program. Connect this pin to an external resistor to program the charge termination current or battery full indication threshold.
9	NTC	Negative Temperature Coefficient (NTC) Thermistor Pin. Connect a $500k\Omega$ resistor from this pin to the IN pin and a $100k\Omega$ NTC resistor (within the battery pack) from this pin to ground. If NTC function is not used, replace NTC resistor with a regular $100k\Omega$ resistor from this pin to ground. <b>Do not leave this pin floating.</b>
10	BATT	Charger Output.



# **TYPICAL PERFORMANCE CHARACTERISTICS**

 $C_{IN}$ =4.7 $\mu$ F,  $C_{OUT}$ =2.2 $\mu$ F,  $V_{IN}$ =5V,  $T_A$ =25°C, unless otherwise noted.





# **TYPICAL PERFORMANCE CHARACTERISTICS**



4.170

4.150

-40

-10

20

Temperature (°C)

50

80

110

V<sub>CHG</sub> 5V/div

 $I_{\rm IN}$ 20mA/div

20ms/div

110

540

530

520

-40

-10

20

Temperature (°C)

50

80



# **BLOCK DIAGRAM**



Figure 1—Functional Block Diagram

## **OPERATION**

#### **Input Voltage Range**

The MP26058 has built-in input voltage surge protection as high as +28V. The charger IC will be automatically disabled when the input voltage is lower than 2.2V or higher than 7.0V. For MP26058, the open-drain pin  $\overrightarrow{\text{ACOK}}$  is used to indicate an input power good condition (i.e.  $2.8V < V_{\text{IN}} < 7.0V$ ). If the input voltage is lower than the battery voltage, the IC is also disabled to prevent the battery from draining.

## Charge Cycle (Mode Change: CC-> LDO)

Figure 2 below shows the typical charging profile for the MP26058. It begins charging at the constant current of the programmed value ( $I_{CHG}$ ). This is referred to as Constant Current (CC) mode. Once the battery voltage reaches 4.2V, the charger will operate in the LDO mode to keep the battery is fully charged. The charge current drops during LDO mode, and the battery full indication is set when the charge

www. yxd163. com

1/25/2010

current reduced to the preset value based on  $R_{BF}$ . After 262144 cycles of continuous charging,



if the battery is still not reaching IBF condition, the on-chip timer will terminate the charger to prevent charging the dead battery for excessive long time and the fault condition will be flagged by flashing the CHG LED.



Figure 2—MP26058 Typical Charging Profile

MP26058-28V, 1A LI + LINEAR BATTERY CHARGER WITH TIMER AND LDO MODE



www.yxd163.com

## MP26058-28V, 1A LI + LINEAR BATTERY CHARGER WITH TIMER AND LDO MODE



MP26058 Rev. 0.91

www.MonolithicPower.com

8

www.yxd163.com



## APPLICATION Flow Chart of Operation

Power-On Reset (POR) feature can be applied to the MP26058 to ensure that the device starts operating in a known state. The flow chart in Figure 4 describes the conditions and operation modes of the MP26058. CVC and CCC stand for "constant voltage charge" and "constant current charge", respectively.



WP26058 Rev. 0.91 WWW. yxd163. com

9



# **PACKAGE INFORMATION**



#### **RECOMMENDED LAND PATTERN**

**NOTICE:** The information in this document is subject to change without notice. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.

www. yxu105. com





www.MonolithicPower.com

10